MSRP: \$125.00 USD

3 Channel Mic Mixer with Phantom Power

Input Impedance:

Voltage Gain:

Bandwidth:

Size:

Weight:

Output Impedance:

Maximum Supply Voltage:

1 lb.

MX310 MIC OUTPUT 12 VDC MIC MIC <u>()</u>_+ 2 3 1 PHNT PWR OUTPUT LEVEL LOW CUT ON=UP МІС PLPLPL LINE ROLLS N ON=DO ω **MADE IN USA** www.rolls.com MorMics **MX310** Three Channel Microphone Mixer clip СН 3 CH₂ CH 3 **CH** 1 PHONES 1/8" LEVEL LEVEL LEVEL INPUT pwr AUX The new MX310 is a 3 channel mono microphone mixer. It has individualy switchable phantom power for each channel and individualy switchable low 0 0 cut filters for each channel. The MX310 MorMics also features a 3.5mm (1/8") headphone output jack for monitoring. The MX310 is built in an all metal chassis and weighs 1 pound. Overall dimension are 5.25" X 3.75" X 1.5". Bottom mounts are **3 Channel Mono Mic Mixer** provided for permanent installations. The MX310 ships with an included 12 Individual Phantom Power VDC external power supply. The output XLR of the MX310 is switchable for mic **Headphone Output** or line level output to make the MX310 match up to almost any appliction. Included - 12 Mic/Line Output Switch VDC ROLLS PS27 external SPECIFICATIONS power supply 600 Ohms 600 Ohms 5968 SOUTH 350 WEST S.L.C., UT 84107 50 dB Line/10 dB Mic 16 VDC .05% typical PHONE: 801-263-9053 20Hz - 20 kHz 5.25" x 3.75" x 1.5" **X** (E

FAX: 801-236-9068 DATA SHEET FOR MX310

www.rolls.com

Size: 5.25" X 3.75" X 1.5"

ROLLS



MADE IN USA 6